

SUPREME TUBE LIST FOR MODEL 400 TUBE TESTER

(SETTINGS FOR APPROXIMATELY 75% OF THE REPLACEMENT TUBE TYPES—FOR OTHER TYPES SEE SEPARATE TUBE LIST BOOKLET)

NON-OCTAL TUBES							NON-OCTAL TUBES							OCTAL TUBES							FUTURE OCTAL TUBES							
Tube Type	Sec. Tests	Fila. Volts Sel.	Fila. Ret. Sel.	Switches "Up"	Meter Circuit Sel.	Qual. Sel.	Tube Type	Sec. Tests	Fila. Volts Sel.	Fila. Ret. Sel.	Switches "Up"	Meter Circuit Sel.	Qual. Sel.	Tube Type	Sec. Tests	Fila. Volts Sel.	Fila. Ret. Sel.	Switches "Up"	Meter Circuit Sel.	Qual. Sel.	Tube Type	Sec. Tests	Fila. Volts Sel.	Fila. Ret. Sel.	Switches "Up"	Meter Circuit Sel.	Qual. Sel.	
1A6/1A6S	All	2.0	1	6	B	37.0	52/51S	All	2.5	1	4, 5	B	15.0	5Z4	All	5.0	2	8	E	2.5	5Z4	All	5.0	2	8	E	2.5	
2A3/2A3H	All	2.5	1	4	E	6.0	56/56S	All	2.5	1	4, 5	B	12.0	6A8	All	6.3	2	7, 8	B	9.0	6A8	All	6.3	2	7, 8	B	9.0	
2A5	All	2.5	1	5, 6	E	17.0	57/57S	All	2.5	1	5, 6	B	8.5	6C5	All	6.3	2	7, 8	B	9.5	6C5	All	6.3	2	7, 8	B	9.5	
2A7/2A7S	All	2.5	1	6, 7	B	8.0	58/58S	All	2.5	1	5, 6	B	9.5	6D5	All	6.3	2	7, 8	B	10.0	6D5	All	6.3	2	7, 8	B	10.0	
5Z3	All	5.0	1	4	E	9.0	71/71A	All	5.0	1	4	C	9.0	6F5	All	6.3	2	7, 8	B	5.5	6F5	Without I.C.	All	6.3	2	7, 8	B	5.5
6A6	All	6.3	1	4, 7	E	6.0	75/75S	All	6.3	1	5, 6	B	6.0	6F5	All	6.3	2	7, 8	B	5.0	6F5	With I.C.	All	6.3	2	7, 8	B	5.0
6A7/6A7S	All	6.3	1	6, 7	B	9.5	76	All	6.3	1	4, 5	B	9.0	6F6	All	6.3	2	7, 8	C	6.5	6F6	All	6.3	2	7, 8	C	6.5	
6B7/6B7S	All	6.3	1	6, 7	B	15.0	77	All	6.3	1	5, 6	B	9.0	6H6	All	6.3	2	4, 7, 8	A	15.0	6H6	All	6.3	2	4, 7, 8	A	15.0	
6C6	All	6.3	1	5, 6	B	9.5	78	All	6.3	1	5, 6	B	10.0	6J7	All	6.3	2	7, 8	B	9.0	6J7	All	6.3	2	7, 8	B	9.0	
6D6	All	6.3	1	5, 6	B	10.0	80	All	5.0	1	4	E	18.0	6K7	All	6.3	2	7, 8	B	10.5	6K7	All	6.3	2	7, 8	B	10.5	
6E5	All	6.3	1	5, 6	B	33.5	83	All	6.0	1	4	F	0	6L6	All	6.3	2	7, 8	E	6.5	6L6	All	6.3	2	7, 8	E	6.5	
6F7/6F7S	All	6.3	1	6, 7	C	7.0	84	All	6.3	1	4, 5	E	3.5	6L7	All	6.3	2	7, 8	B	4.5	6L7	All	6.3	2	7, 8	B	4.5	
6Z4	All	6.3	1	4, 5	E	3.5	85	All	6.3	1	5, 6	B	8.0	6Q7	All	6.3	2	7, 8	B	8.5	6Q7	All	6.3	2	7, 8	B	8.5	
12Z3	All	12.6	1	3, 4	E	6.0	485	All	3.3	1	4, 5	B	9.0															
25Z5	All	25.0	1	3, 4, 6	E	2.0																						
01A	All	5.0	1	4	B	47.0																						
19	All	2.0	1	6	B	8.5																						
24/24A	All	2.5	1	4, 5	C	8.0																						
26	All	1.5	1	4	B	31.0																						
27/27S	All	2.5	1	4, 5	B	15.0																						
30	All	2.0	1	4	B	43.5																						
32/32S	All	2.0	1	4	B	32.0																						
33/33S	All	2.0	1	5	C	9.5																						
34/34S	All	2.0	1	4	B	30.5																						
35/35S	All	2.6	1	4, 5	B	15.0																						
36/36A	All	6.3	1	4, 5	B	15.0																						
37/37A	All	6.3	1	4, 5	B	10.5																						
38/38A	All	6.3	1	4, 5	B	9.0																						
39/39A	All	6.3	1	4, 5	C	6.0																						
41/41S	All	6.3	1	5, 6	E	13.0																						
42/42S	All	6.3	1	5, 6	E	11.0																						
43/43C	All	25.0	1	5, 6	E	9.5																						
44	All	6.3	1	4, 5	C	6.0																						
45	All	2.5	1	4	E	19.0																						
46/46S	All	2.5	1	5	E	14.0																						
47/47S/PZ	All	2.5	1	5	E	15.5																						

SUPREME INSTRUMENTS CORPORATION
GREENWOOD, MISSISSIPPI, U. S. A.



www.StevenJohnson.com

**Antique Technolgy, Tube Radios and Test Equipment
Vintage Schematics, and Publications**

Steve's Antique Technology